

Functional and Structural Implications of Non-Separability of Spectral and Temporal Responses in AI

Jonathan Z. Simon
David J. Klein
Didier A. Depireux
Shihab A. Shamma

Institute for Systems Research
and Dept. of Electrical & Computer Engineering
University of Maryland

Supported in part by
MURI # N00014-97-1-0501 from the Office of Naval Research,
NIDCD T32 DC00046-01 from the National Institute on Deafness and Other Communication Disorders,
NSFD CD8803012 from the National Science Foundation.
This poster is available at <<http://www.isr.umd.edu/CAAR/pubs.html>>.

Report Documentation Page				Form Approved OMB No. 0704-0188	
Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.					
1. REPORT DATE 2000		2. REPORT TYPE		3. DATES COVERED 00-00-2000 to 00-00-2000	
4. TITLE AND SUBTITLE Functional and Structural Implications of Non-Separability of Spectral and Temporal Responses in AI				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S)				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) University of Maryland, Department of Electrical Engineering and Computer Engineering, Institute for Systems Research, College Park, MD, 20742				8. PERFORMING ORGANIZATION REPORT NUMBER	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution unlimited					
13. SUPPLEMENTARY NOTES					
14. ABSTRACT					
15. SUBJECT TERMS					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT Same as Report (SAR)	18. NUMBER OF PAGES 20	19a. NAME OF RESPONSIBLE PERSON
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified			

Introduction

- We measure the response of cells in ferret Primary Auditory Cortex (AI) to dynamic, broadband sounds.
- The dynamic, broadband sounds are simple combinations of spectro-temporal basis functions, called “moving ripples.”
- By correlating the response with the stimulus, we derive Spectro-Temporal Receptive Fields (STRFs), a linear, quantitative descriptor of how a cell responds to dynamic sounds.
- The STRFs exhibit symmetries and patterns such as separability, and its generalization, quadrant separability.
- Quadrant separability does not arise from most neural networks, and can be used to rule out some models of neural connectivity.


Summary

- The STRFs measured for all units in AI are quadrant separable or fully separable.
- Quadrant separability is **incompatible** with simple summing of independent, fully separable sources.
- Summing two fully separable STRFs is quadrant separable if the temporal processing is in quadrature.
- There are three ways in which a fully separable STRF can become quadrant separable:
power asymmetry, *spectral* asymmetry, & *temporal* asymmetry.
- Only power and spectral asymmetry contribute to quadrant separability in AI, **not temporal**.
- Quadrant Separability is incompatible with velocity selectivity.
- Quadrant Separability and persistence of temporal symmetry strongly constrain possible models of neural connectivity.


STRFs in AI

Cells are characterized their Spectro-Temporal Response Field (STRF)...

... or by the (Fourier domain) ripple Transfer Function (TF).



Moving ripples form the basis for the Fourier domain description of dynamic spectra. At time t and frequency x , the amplitude $S(t,x)$ is given by:



$$S(t,x) = \sin(2\pi w t + 2\pi \Omega x + \Phi)$$


$$x = \log_2[f/f_0]$$

w = ripple velocity, modulation rate


Ω = ripple frequency, spectral density

Temporally Orthogonal Ripple Combinations


- STRF measured by reverse-correlating with dynamic spectrum of a broad-band stimulus.
- Temporally Orthogonal Ripple Combinations composed of ripples with different modulation rates.
- Allow clean STRF estimates in relatively short time.



The stimuli shown contain ripples covering the same range of ripple velocities, but at different ripple frequencies.



Fully Separable STRF



The STRF and TF are a product of a single spectral response function with a single temporal response function.

Shown above are the impulse responses $f(t)$ and receptive fields $g(x)$ derived from quadrant 1 (black) and quadrant 2 (red) of the transfer function by inverse Fourier transformation.


$$STRF(t, x) = f(t) g(x)$$

$$f(t) \xleftrightarrow{|\mathcal{F}\{\cdot\}|} F(w)$$

$$g(x) \xleftrightarrow{|\mathcal{F}\{\cdot\}|} G(\Omega)$$


$$TF(w, \Omega) = F(w) G(\Omega)$$

Quadrant Separable STRF



This neuron responded twice as strong to rising frequencies than it did to falling frequencies.

$$\begin{aligned} f_i(t) &\xrightarrow{|\mathcal{F}\{\cdot\}|} F_i(w) \\ g_i(x) &\xrightarrow{|\mathcal{F}\{\cdot\}|} G_i(\Omega) \end{aligned}$$




The STRF is not separable, but each quadrant of the transfer function is, i.e., there are different spectral and temporal responses for upwards and downwards frequency modulation.

$$T(w, \Omega) = \begin{cases} F_1(w) G_1(\Omega) & w > 0, \Omega > 0 \\ F_2(w) G_2(\Omega) & w < 0, \Omega > 0 \end{cases}$$


$$\text{and for } \Omega > 0: T(w, \Omega) = T^*(-w, -\Omega)$$

Examples & Counterexamples


Fully
Separable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Quadrant
Separable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow



Velocity
Selective
is
Inseparable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Quadrant
separability is
incompatible
with velocity
selectivity.

A Counterexample


Fully
Separable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Fully
Separable
(displaced)




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow



Sum of two
Fully
Separable
is
Inseparable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Naive sum of
two fully
separable
STRFs is
inseparable.

An Example


Fully
Separable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Same Fully
Separable
but Lagged
(& shifted
spectrally)




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow



Sum of
Non-Lagged
and Lagged
is
Separable




$|\mathcal{F}\{\cdot\}|$
 \longleftrightarrow




Sum of two
fully separable
STRFs is
separable if
the temporal
processing is
in quadrature.

Measuring Separability with SVD

- Singular Value Decomposition (SVD) can be used to estimate the separability of a Transfer Function (possibly corrupted by noise). It decomposes the Transfer Function into a sum of Quadrant Separable Transfer Functions, ordered by their power.
- We apply SVD to each quadrant of the transfer function. Below, an STRF and the three most significant quadrant-separable components, derived from SVD:



SVD Example



- SVD naturally picks out high SNR components of a matrix.
- Large jumps in the singular values separate signal from noise.
- Jumps straddle bootstrap estimate of noise.
- Noise can be removed by discarding lower-magnitude components.
- All cells (31) measured in AI have a single dominant SVD component in each quadrant.


All units measured in AI are quadrant separable (or fully separable).

Measure of Inseparability

- SVD supplies a natural measure of inseparability, α_{SVD}

$$\alpha_{\text{SVD}} = \left(1 - \frac{\lambda_1^2}{\sum_i \lambda_i^2} \right)$$

- $\alpha_{\text{SVD}} \approx 0$ is fully separable
- $\alpha_{\text{SVD}} > 0.3$ is strongly inseparable



Symmetry by Power

- α_d : Power asymmetry breaks full separability, producing quadrant separability

$$\alpha_d = (P_1 - P_2)/(P_1 + P_2)$$

$$P_1 = (\text{Power in quadrant 1}) = (\lambda_1)^2$$




$$P_2 = (\text{Power in quadrant 2}) = (\lambda_2)^2$$

- $\alpha_d \approx 0$ is symmetric in power
- $|\alpha_d| > 0.3$ is quite asymmetric in power—strongly inseparable

Example STRF

Population Statistics

Contribution to α_{SVD}



Spectral Symmetry


- α_s : Asymmetry between spectral cross-sections $G_i(\Omega)$:

$$\alpha_s = 1 - \left| \frac{\sum_{\Omega > 0} G_1(\Omega) G_2^*(\Omega)}{\sqrt{\sum_{\Omega > 0} |G_1(\Omega)|^2 |G_2(\Omega)|^2}} \right|$$


where the quantity inside the big absolute value bars is the (complex) correlation between $G_1(\Omega)$ and $G_2(\Omega)$

- $\alpha_s \approx 0$ is spectrally symmetric
- $\alpha_s > 0.3$ is spectrally asymmetric—strongly inseparable


Example STRF



Population Statistics



Contribution to α_{SVD}






Temporal Symmetry

- α_t : Asymmetry between temporal cross-sections $F_i(w)$:

$$\alpha_t = 1 - \frac{\left| \sum_{w>0} F_1(w) F_2(-w) \right|}{\sqrt{\sum_{w>0} |F_1(w)|^2 |F_2(-w)|^2}}$$

where the quantity inside the big absolute value bars is the (complex) correlation between $F_1(w)$ and $F_2^*(-w)$


- $\alpha_t \approx 0$ is temporally symmetric
- $\alpha_t > 0.3$ is temporally asymmetric—strongly inseparable






Distribution is strongly skewed toward temporal symmetry.

Symmetry Correlations


- Mean of 3 separate symmetry measures correlates well with full separability index.




- Individual indices only partially correlated with each other.



Models









Not Quadrant Separable



Quadrant Separable

Example STRF Recording Pairs



*Very similar,
Both fully separable*

*Different,
Upper fully separable,
Lower quadrant separable*

*Very different,
Both quadrant separable
(somewhat noisy though)*

$$\varepsilon = (20\%, 15\%) \quad \alpha_s^{\text{corr}} = \begin{bmatrix} 4\% & 6\% \\ 3\% & 4\% \end{bmatrix}$$

$$\alpha_t^{\text{corr}} = \begin{bmatrix} 2\% & 7\% \\ 4\% & 5\% \end{bmatrix}$$

$$\varepsilon = (40\%, 25\%) \quad \alpha_s^{\text{corr}} = \begin{bmatrix} 6\% & 10\% \\ 23\% & 12\% \end{bmatrix}$$

$$\alpha_t^{\text{corr}} = \begin{bmatrix} 6\% & 5\% \\ 20\% & 7\% \end{bmatrix}$$

$$\varepsilon = (60\%, 60\%) \quad \alpha_s^{\text{corr}} = \begin{bmatrix} 32\% & 55\% \\ 40\% & 25\% \end{bmatrix}$$

$$\alpha_t^{\text{corr}} = \begin{bmatrix} 21\% & 32\% \\ 27\% & 59\% \end{bmatrix}$$

Selected References

Spectro-Temporal Correlation Methods

- Klein DJ, Depireux DA, Simon JZ and Shamma SA, Robust spectro-temporal reverse correlation for the auditory system: Optimizing stimulus design, J. Computational Neurosci. 2000.
- Eggermont JJ, Hearing Research 66 (1993) 177-201.

Singular Value Decomposition

- Hansen PC, Rank-Deficient and Discrete Ill-Posed Problems, SIAM 1998.
- Press WH, Flannery BP, Teukolsky SA, and Vetterling, WT, Numerical Recipes, Cambridge University Press 1986.

Separability

- Watson AB and Ahumada AJ, J. Opt. Soc. Am. A2(2) (1985) 322–341.
- Saul AB and Humphrey AL, J. Neurophysiol. 64 (1990) 206-224.

Related techniques and models

- Kowalski N, Depireux D and Shamma S, J. Neurophysiol. 76 (5) (1996) 3503-3523, & 3524-3534.
- Depireux DA, Simon JZ and Shamma SA, Comments in Theoretical Biology (1998).
- Wang K and Shamma SA, IEEE Trans. on Speech and Audio 2(3) (1994) 421-435, and 3(2) (1995) 382-395.

Special thanks to Steve Bierer for his help in spike sorting.